

Dlink DSL-2740B

Please follow the below steps to configure Dlink DSL-2740B modem

- Establish a connection between the device and the router via network cable or Wi-Fi (if there's a WIFI password you have to check bottom of the router. If you turn the router over, you should see a sticker, and one of the pieces of information should say something like "Wi-Fi Password" or "WPA passcode.")
- Open a browser and type 192.168.1.1 in the address bar
- You will be prompted to enter Username: admin and Password: admin

D-Link

LOGIN

Log in to the router

User Name : admin

Password :

Log In

BROADBAND

- After logging in , Click Setup and Internet Setup then under ADSL Interface click Setup

DSL-2740B // **SETUP** **ADVANCED** **MAINTENANCE** **STATUS**

Internet Setup **←**

Wireless Setup

LAN Setup

Time and Date

Parental Control

Wireless Schedule

Logout

Internet Offline

English

Reboot

INTERFACE SETUP

There are 2 ways to setup your internet. You can use ADSL to configure the internet or you can assign one of the Ethernet ports as a WAN port to internet.

ADSL INTERFACE

Use ADSL interface to setup your internet.

Setup **←**

ETHERNET WAN INTERFACE

Assign one of the Ethernet ports as a WAN port to internet.

Setup

- When ADSL Setup page opens , Click Setup Wizard

SETUP	ADVANCED	MAINTENANCE	STATUS
ADSL SETUP			
<p>If you are configuring this device for the first time, D-Link recommends that you click Setup Wizard button, and follow the instructions on screen. If you wish to modify or configure the ADSL settings manually, tick Manual Setup to enable the ADSL Connection Setup.</p>			
 <input type="button" value="Setup Wizard"/> <input type="checkbox"/> Manual Setup			

- There are 3 steps to configure the device. Click Next to continue

SETUP	ADVANCED	MAINTENANCE	STATUS
WELCOME TO D-LINK SETUP WIZARD			
<p>This wizard will guide you through a step-by-step process to configure your new D-Link router and connect to the Internet.</p>			
<ul style="list-style-type: none">• Step 1: Change your DSL-2740B router password• Step 2: Select Internet connection• Step 3: Restart			
 <input type="button" value="Next"/> <input type="button" value="Cancel"/>			

- Click Skip to avoid changing admin password of modem's interface

SETUP	ADVANCED	MAINTENANCE	STATUS
STEP 1: CHANGE YOUR DSL-2740B PASSWORD			
<p>The factory default password of this router is 'admin'. To help secure your network, D-Link recommends that you should choose a new password. If you do not wish to choose a new password now, just Click Skip to continue. Click Next to proceed to next step.</p>			
<p>Current password : <input type="text"/></p>			
<p>New password : <input type="text"/></p>			
<p>Confirm password : <input type="text"/></p>			
 <input type="button" value="Back"/> <input type="button" value="Next"/> <input type="button" value="Skip"/> <input type="button" value="Cancel"/>			

- Select Others as Country and ISP Provider
- Type VPI and VCI , VPI should be 0 if DSP is Ogero and 8 if DSP is GDS while VCI should be 35
- Select PPPoE LLC/Snap-Bridging as Connection type then click Next

SETUP	ADVANCED	MAINTENANCE	STATUS
STEP 2: SELECT INTERNET CONNECTION TYPE			
Please select your Country and ISP (Internet Service Provider) from the list below. If your Country or ISP is not in the list, please select "Other".			
<div style="border: 1px solid red; padding: 5px;"><p>Country : <input type="text" value="Others"/></p><p>ISP Provider : <input type="text" value="Others"/></p><p>VPI : <input type="text" value="0"/></p><p>VCI : <input type="text" value="35"/></p><p>Connection Type : <input type="text" value="PPPoE LLC/Snap-Bridging"/></p></div>			
<input type="text" value="PPPoE LLC/Snap-Bridging"/> <input type="button" value="Back"/> <input type="button" value="Next"/> <input type="button" value="Cancel"/>			

- Type ADSL Username and Password then click Next

STEP 2: SELECT INTERNET CONNECTION TYPE			
Please enter your Username and Password as provided by your ISP (Internet Service Provider). Please enter the information exactly as shown taking note of upper and lower cases. Click Next to continue.			
Username : <input type="text" value="D??????@idm.net.lb"/>			
Password : <input type="text" value="*****"/>			
Confirm Password : <input type="text" value="*****"/>			
<input type="button" value="Back"/> <input type="button" value="Next"/> <input type="button" value="Cancel"/>			

- Click Apply to save configuration and reboot modem

STEP 3: RESTART

Setup complete. Click Back to review or modify settings. Click Restart to apply current settings and reboot the router. If your Internet connection does not work after restart, you can try the Setup Wizard again with alternative settings or use Manual Setup instead if you have your Internet connection details as provided by your ISP.



- To configure Wireless Settings , click Setup then Wireless Setup and choose Manual Wireless Connection Setup

DSL-2740B	SETUP	ADVANCED	MAINTENANCE	STATUS
Internet Setup	WIRELESS CONNECTION			
Wireless Setup 	There are 2 ways to setup your wireless connection. You can use the Wireless Connection Setup wizard or you can manually configure the connection.			
LAN Setup	Please note that changes made on this section will also need to be duplicated to your wireless clients and PC.			
Time and Date	WIRELESS CONNECTION SETUP WIZARD			
Parental Control	If you would like to utilize our easy to use Web-based Wizard to assist you in connecting your new D-Link Systems Wireless Router to the Internet, click on the button below.			
Wireless Schedule	<input type="button" value="Wireless Connection Setup Wizard"/>			
Logout	Note: Before launching the wizard, please make sure you have followed all steps outlined in the Quick Installation Guide included in the package.			
	ADD WIRELESS DEVICE WITH WPS(WI-FI PROTECTED SETUP) WIZARD			
English 	This wizard is designed to assist you in connecting your wireless device to your router. It will guide you through step-by-step instructions on how to get your wireless device connected. Click the button below to begin.			
<input type="button" value="Reboot"/>	<input type="button" value="Add wireless Device with WPS"/>			
	MANUAL WIRELESS CONNECTION OPTIONS			
	If you would like to configure the Internet settings of you new D-Link Router manually, then click on the button below.			
	<input type="button" value="Manual Wireless Connection Setup"/> 			

 Activate Windows
Go to Settings to activate

- Make sure Wireless adapter is enabled then in Wireless Network Name (SSID) type wireless name and scroll down to Wireless Security Mode

DSL-2740B	SETUP	ADVANCED	MAINTENANCE	STATUS
Internet Setup	WIRELESS			
Wireless Setup	Use this section to configure the wireless settings for your D-Link router. Please note that changes made on this section will also need to be duplicated to your wireless clients and PC.			
LAN Setup	WIRELESS SECURITY WIZARD			
Time and Date	If you are setting up your wireless network for the first time, D-Link recommends that you click the Secure my Wireless Network button and follow the step by step instructions.			
Parental Control	<input type="button" value="Secure My Wireless Network"/>			
Wireless Schedule	WIRELESS NETWORK SETTINGS			
Logout	Enable Wireless : <input checked="" type="checkbox"/>  Wireless Network Name (SSID) : <input type="text" value="dlink"/>  Wireless Channel : <input type="text" value="1"/> 802.11 Mode : <input type="text" value="Mixed 802.11n, 802.11g and 802.11b"/> Channel Width : <input type="text" value="Auto 20/40 MHz"/> Transmission Rate : <input type="text" value="Best (automatic)"/> (Mbit/s) Hide Wireless Network : <input type="checkbox"/>			
 English <input type="button" value="v"/> <input type="button" value="Reboot"/>	WIRELESS SECURITY MODE			

- Select Auto(WPA or WPA2) as security Mode

WIRELESS SECURITY MODE
<p>To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP, WPA, WPA2 and Auto.</p> <p>The WEP mode is the original wireless encryption standard. WPA provides a higher level of security.</p> <p>For maximum compatibility, use WPA. This mode uses TKIP cipher. Some gaming and legacy devices work only in this mode. For best security, use WPA2 mode. This mode uses AES(CCMP) cipher and legacy stations are not allowed access with WPA security. Use Auto(WPA or WPA2) mode to achieve a balance of strong security and best compatibility. This mode uses WPA for legacy clients while maintaining higher security with stations that are WPA2 capable. Also the strongest cipher that the client supports will be used</p> <p>To achieve better wireless performance use WPA2 security mode (or in other words AES cipher).</p> <p>Security Mode : <input type="text" value="Auto (WPA or WPA2)"/> (TKIP or AES) </p>

- Select WPA/WPA2-PSK Personal as WPA Mode and in Pre-Shared Key type wireless password then Click Apply Settings (safest passwords are long and contain at least 8 digits of mixed letters, and numbers)

AUTO (WPA OR WPA2)

WPA-Personal does not require an authentication server. The WPA-Enterprise option requires an external RADIUS server

WPA Mode : ←

Group Key Update Interval : (seconds)

PRE-SHARED KEY

Pre-Shared Key : ←

Please take note of your SSID and security Key as you will need to duplicate the same settings to your wireless devices and PC.

→